



TOLERANCES  
MOUNTING CENTERS =  $\pm .06"$   
MOUNTING HOLE SIZE =  $\pm .005"$

THIS DRAWING CONTAINS PROPRIETARY INFORMATION  
BELONGING TO HAMMOND POWER SOLUTIONS INC.,  
AND IS NOT FOR GENERAL DISTRIBUTION

All Dimensions in Inches  
mm in Parenthesis

REACTOR

**hammond** HPS CENTURION R  
POWER SOLUTIONS 3PH DRY TYPE  
REACTOR  
CRX0022BC  
2.1MH 50/60 HZ 22 AMPS  
0.6 KV CLASS TEMP CLASS: 130 TYPE JR-1  
TERMINAL TORQUE: 11 LB-IN AMBIENT: 50°C

f003781e

NOTES:



TITLE: 3 PHASE LINE REACTOR

				DES: PBAKER
				DATE: 14/06/25
NO.	DATE	BY	REVISION	SCALE: NTS

SHEET 1 OF 1

EDBCRX0022BC

0.1 wed 2023/08/17 19:06